



DSX Access Systems, Inc.

CAC Enrollment Reader



- **USB Connected**
- **Programmed by DSX**
- **Formatted for DSX SQL**
- **Reads FIPS 201 and CAC Cards**
- **Inserts 16 digit CHUID in Code field / 75 or 200 bit**
- **LED flashes and beeps when card is read**

CAC Enrollment Reader

Size

4.2"W x 2.5"H x .875"D

Weight

.45lbs

Power Requirements

USB

Warranty

Limited 1 Year

13.56 MHZ / FCC, RoHS

CAC Enrollment Reader

USB connected Reader. This reader is preprogrammed by DSX to properly read the CAC card and insert the proper data into the DSX SQL database.

Requirements

FIPS 201 Enrollment Reader that is formatted by DSX for DSX SQL.

Requires DSX SQL version 4.8.75 or higher.

75 bit - Device Type T5 – No Issue Level
200 bit - Device Type V6 – Issue Level -
(recommended)

Connections

Connect Enrollment Reader to a USB Port on a Client PC running DSX SQL.

Enrollment Process

Add or Edit a card holder. Advance to the Card screen and click on the Code field.

Once the cursor is in the Code field – Present the Card to the Reader in the same orientation until it beeps.

Card Holder, New New Card

Cards | Access Level: | Linking Level: |

Code #: 1234567890123456 P.I.N.#: []

Imprinted Card #: [] # of Uses Allowed: 9999

Start Date: 3/22/2018 Stop Date: 4/28/2019

Start Time: 12:00:00 AM Stop Time: 12:00:00 AM

Guard Tour: Override Anti-Passback:

Status:

Date Last Used: 1/1/1000 Anti-PassBack Status: [N] [N] [N] [N]

Last Used At: Loc: 1 00 Interior Tower Sliding Door

Notes: []

Previous Next Cancel OK

Once the Card is presented, the data is placed in the Code field. Finish entering the other pertinent data and Click OK to Save.

(Other Enrollment Readers are available from DSX to properly read different types and formats of Cards.)